



## PSR-B

**Brand:** Landscape Irrigation

**Product Line:** Controllers

**Product Model:** Pump Start Relay

**SKU:** PSRB

**Description:** Pump Start Relay Booster, used to boost controller output power to operate larger pump start relays, if required

### Shipping Information

**UPC-A:** 0611698146071

**Qty. / Bag:** 8

**Origin:** ASSEMBLED IN MALAYSIA

**Ocean Pallet:** 1664

**Land Pallet:** 1280

**Master Carton:** 8

### Additional Information

**Approvals:** IP54

**Approvals:** [IP54](#)

Pump Start Relay Electrical Specifications									
Models	Single Phase		3 Phase**	Max. Full Load Amps	Max. Resistive Amps	Coil VA		Coil VA	
	kW at 120 VAC	kW at 230 VAC	kW at 230 VAC			Inrush	(Amps)	Holding	(Amps)
PSR-22	1.5*	2.2*	N/A	30	40	33	(1.38)	8	(0.33)
PSR-52	2.2	5.6	N/A	40	50	65	(2.71)	7.5	(0.31)
PSR-53	2.2	5.6	7.5	40	50	65	(2.71)	7.5	(0.31)
<b>Note:</b> *Approximate power ** 3 phase power at 230 VAC is not commonly available in some international markets. Check local electrical codes for compatibility.									

Copyright © 2025 Hunter Industries Inc. Hunter, the Hunter logo, and other marks are trademarks of Hunter Industries Inc., registered in the U.S. and certain other countries.

<https://api.hunterirrigation.com/en-metric/irrigation-product/pump-start-relay/psr-b>  
121625