ROAM LR

Add professional, licence-free remote control to projects of any size with this long-range device.

KEY BENEFITS


- Compatibility with Hunter X2[™], Pro-C®, HPC, HCC, ICC2, ACC2, and legacy ACC and I-Core[™] Controllers to enable remote management for projects of any size
- Manually start individual stations or programs for quick maintenance checks and troubleshooting
- 128 available programmable addresses prevent cross-communication between multiple remotes within close proximity of each other
- Programmable run times from 1 to 90 minutes, which will not overwrite regular automatic programming
- Manual operation up to 240 stations provides flexibility for larger projects
- Rugged and water-resistant transmitter with simple push-button operation and a battery-life indicator
- Achieve a 3.2 km line of site range with licence-free 915 MHz LoRa radio technology



ROAM-LR-R

- Range: 3.2 km line of sight from transmitter to receiver
 Transmitter power source: 4 AAA batteries (included)
- Receiver source: 24 VAC, 0.10 A
- System operating frequency: 915 MHz
- SmartPort® Wiring Harness installation: 15.2 m from controller
- Approvals: IP55 rating for transmitter and receiver (when installed on controller)
- FCC approved (not available in EU and some other countries; check local regulations)

Warranty period: 3 years



Receiver unit (SmartPort Wiring Harness included)

Copyright © 2025 Hunter Industries Inc. Hunter, the Hunter logo, and other marks are trademarks of Hunter Industries Inc., registered in the U.S. and certain other countries.