



## PSR-B

**Brand:** Landscape Irrigation

**Product Line:** Controllers

**Product Model:** Pump Start Relay

**SKU:** PSRB

**Description:** Pump Start Relay Booster, used to boost controller output power to operate larger pump start relays, if required

---

## Shipping Information

**UPC-A:** 0611698146071

**Qty. / Bag:** 8

**Ocean Pallet:** 1664

**Land Pallet:** 1280

**Master Carton:** 8

Pump Start Relay Electrical Specifications

Models	Single Phase		3 Phase**	Max. Full Load Amps	Max. Resistive Amps	Coil VA		Coil VA	
	HP at 120 VAC	HP at 230 VAC	HP at 230 VAC			Inrush	(Amps)	Holding	(Amps)
PSR-22	2*	3*	N/A	30	40	30	(1.25)	6.5	(0.27)
PSR-52	3	7.5	N/A	40	50	60	(2.50)	5	(0.21)
PSR-53	3	7.5	10	40	50	60	(2.50)	5	(0.21)

**Note:**

\* Approximate power

\*\* 3 phase power at 230 VAC is not commonly available in some international markets. Check local electrical codes for compatibility.

Copyright © 2026 Hunter Industries Inc. Hunter, the Hunter logo, and other marks are trademarks of Hunter Industries Inc., registered in the U.S. and certain other countries.

<https://api.hunterirrigation.com/irrigation-product/pump-start-relay/psr-b>  
020226